

marantz



AMP 20

AMP 20 12-Channel Power Amplifier

Reference 12-Channel 200-watt-per-channel power amplifier. Pair with AV 20 to create an elite-level home theater. Marantz HDAM, Current Feedback Amplification, and balanced line level input.

Detailed and immersive sound transforms your home theater

200 watts per channel into 8Ω / 400 watts per channel into 4Ω

12 channels powers large home theaters

Bi-amp mode drives high- and low-frequency sections of loudspeakers independently

BTL Mode (Bridge mode) combines two channels into a single 400-watt per channel into 8Ω

Perfect match for Marantz AV 20 preamplifier

Balanced XLR input is ideal for reducing input noise

Porthole with analog meter measures output

Soft side lights cast a warm glow on the front surface of the amplifier

Elegant design matches rich, warm sound



The Most Musical Sound

AMP 20

Technical Specifications

| Inputs/Outputs | | |
|---|-----------------------------|--|
| Audio | Main Amplifier In | Balanced & Unbalanced: 12ch (Exclusive use by a selector switch.) |
| Other | Speaker Terminal | SPKT-1+ |
| | Number of Speaker Terminals | 12 |
| | Bi-Amp Drive / BTL Drive | Yes / Yes |
| | Level Meter | Yes |
| Chassis | | Copper Plated |
| Multi-Room | | |
| RS232 Control | | Yes |
| IR Flasher In | | Yes |
| Marantz Remote Bus | | Yes |
| DC Trigger Input / Output | | 1 / 1 |
| Specifications | | |
| Number of Power Amps | | 12 |
| Power Output (8 ohm, 1 kHz, 0.05% 2ch Drive) Normal / BTL | | 200W / 400W |
| Power Output (4 ohm, 1 kHz, 0.7% 2ch Drive) Normal | | 400W |
| Power Output (8 ohm, 1 kHz, 0.7% 5ch Drive) Normal | | 200W |
| General | | |
| Front Display | | Level Meter |
| Auto Power Off | | Yes |
| Metal Front Panel | | Yes |
| Power Consumption | | 400W |
| Power Consumption, No-Sound | | 110W |
| Standby Consumption | | 0.2W |
| Maximum Dimensions (W × D × H) | | 17.4 × 17.4 × 7.5 in. |
| Weight | | 39.7 lbs |
| What's in the Box | | Main unit, quick start guide, AC cord,Amp control cable, Remote control cable, SP terminal wrench |
| UPC Code | | 747192143930 |
| Limited Warranty (United States and Canada) | | 5-year |



Design and specifications are subject to change by Marantz without notice.

